

## Mains Operation & Resulting Temperature Table and Mains Fusing TGX-Amplifiers

<b>TGX10</b>	<b>U mains [V] (5)</b>	<b>I mains [A]</b>	<b>P mains [W]</b>	<b>P out [W]</b>	<b>Pd [W] (4)</b>	<b>BTU/hr (3)</b>
Standby	230	0.61	18	0	18	61
Idle	230	0.75	80	0	80	273
1/8 Max. Output Power @ 8 Ω (2)	230	4.60	850	4 x 156	226	771
1/8 Max. Output Power @ 4 Ω (2)	230	8.50	1700	4 x 313	448	1529
1/8 Max. Output Power @ 2 Ω (2)	230	9.50	2100	4 x 325	800	2730
Nominal Operation Mode @ 4 Ω (1)	230	5.73	1200	4 x 188	448	1529

<b>TGX20</b>	<b>U mains [V] (5)</b>	<b>I mains [A]</b>	<b>P mains [W]</b>	<b>P out [W]</b>	<b>Pd [W] (4)</b>	<b>BTU/hr (3)</b>
Standby	230	0.63	19	0	19	65
Idle	230	0.94	110	0	110	375
1/8 Max. Output Power @ 8 Ω (2)	230	8.75	1730	4 x 313	478	1631
1/8 Max. Output Power @ 4 Ω (2)	230	16.70	3450	4 x 625	950	3242
1/8 Max. Output Power @ 2 Ω (2)	230	18.70	4150	4 x 650	1550	5289
Nominal Operation Mode @ 4 Ω (1)	230	10,90	2250	4 x 375	750	2559

(1) Sine Modulation (1 kHz)

(2) Pink Noise according to EN60065 / 8. Edition

(3) 1 BTU = 1055.06 J = 1055.06 Ws

(4) Pd = Power Dissipation

(5) The following conversion factors can be used for easy conversion of mains current:

100 V = 2.3; 120 V = 1.9; 240 V = 0.96

### Recommended Mains Fusing and Mains Cable Diameter for TGX Amplifiers

Amp Model	Rating of mains breaker (1)	Mains Cable Cross-Section (1), (2)
<b>TGX10</b>	13 A - 16 A (208 V - 240 V) 30 A (100 V - 120 V)	3 x 1.5 mm <sup>2</sup> - 3 x 2.5 mm <sup>2</sup> (AWG14) AWG12 (3 x 3.3 mm <sup>2</sup> )
<b>TGX20</b>	16 A (208 V - 240 V) 30 A (100 V - 120 V) 30 A (208 V) (3) 32 A (220 V - 240 V) (3)	3 x 1.5 mm <sup>2</sup> - 3 x 2.5 mm <sup>2</sup> (AWG14) AWG12 (3 x 3.3 mm <sup>2</sup> ) AWG12 (3 x 3.3 mm <sup>2</sup> ) 3 x 4.0 mm <sup>2</sup>

Important Notes:

- (1) Additional and/or other requirements from local authorities may apply.
- (2) The detachable power supply cord must be an approved type acceptable to the authorities of the respective country. The maximum recommended length of the power supply cord set is 5 m (16 ft).
- (3) Preferred operation mode for TGX20 for high power subwoofer applications.